


product description: intended for installation to the distribution of low voltage
 standard shape
 designed for wall or ceiling mounting
 possibility to install in places with risk of flammable gases and vapor – danger zone 2
 possibility to install in places with explosive risk of dust – danger zone 22
 the _P2 configuration - adhesive tape on the back side for easier fixing of the trunking before final installation to the substrate material

material: PVC - Pb-free
 self-snuffing: yes, within 30 s
 temperature resistance: -5 - +60 °C
 flaming loop test: 850 °C
 impact strength: 0,5 J
 protection types: IP20
 fire class for underlying material: A1-F
 inside area: 50 mm²
 distance base perforation: 200 ±20 mm
 length tolerance: ±10 mm
 weight: 0,07 kg/m
 meets the requirements: EN 50085-1 ed.2:06, EN 50085-2-1:07
 storage: ČSN 64 0090



chemical resistance: YES: amoniak 25%, distilled water, ethanol 50%, sodium hydroxide 60%, hydrofluoric acid 40%, acetic acid 5%, sulfuric acid 96%, medicinal oil, methanol, olive oil, petroleum, hydrogen peroxide 20%, transformer oil, sodium carbonate
 NO: aceton, benzen, chlorinated hydrocarbons, tetrachlorocarbon

trunkings are not a breeding ground for bacteria, tested in SZÚ according to ČSN EN ISO 846:2019

list of bacteria that have been tested:

ESCHERICHIA COLI, STAPHYLOCOCCUS AUREUS, KLEBSIELLA PNEUMONIAE, PSEUDOMONAS AERUGINOSA, ENTEROCOCCUS FAECALIS, BACILLUS SUBTILIS, SALMONELLA ENTERICA, LEGIONELLA PNEUMOPHILA, CANDIDA ALBICANS

item number	length	color	package	package - description	note
LV 11X10_HD	2 m	white RAL 9003	150 m	carton	-
LV 11X10_P2	2 m	white RAL 9003	150 m	carton	self-adhesive tape

recycling symbols:



PVC trunkings, PVC covers



Protective film, adhesive tape, packaging film for trunkings, bags, and packaging film for covers



cardboard

Risks Associated with Product Use:

during installation, use appropriate protective work equipment and follow safety guidelines
use the product only for the purposes intended by the manufacturer
use the product in an environment that complies with the manufacturer's instructions
do not use the product if it is damaged
follow the manufacturer's recommendations and do not exceed the number of inserted cables or the product's load capacity
after installation, check the correctness of the mounting of trunkings and covers according to the manufacturer's recommendations